

## Genset Model

C1675 D5A, 1675kVA Standby, 1500kVA Prime, KTA50Gs8, Diesel, Open  
Specified Origin of Critical Components is not required  
Emergency Standby Power (ESP)  
Emissions Level : No Certification  
Local Codes and/or Regulation : CE  
Output Voltage : 400/230, 3 Phase, Wye, 4 Wire

## Engine

KTA50Gs8  
Engine Air Cleaner - Duty Rating : Normal Duty  
Engine Coolant Heater : 240V

## Sub-Base Anti-Vibration Mounts

None Supplied

## Main Generator

P7LVD, 6 Leads, 50 Hertz (Hz), 380 - 440V, 150C, Emergency Standby Power (ESP)  
Generator Accessories  
Voltage Regulator - PMG  
Main Generator Heater : 240V

## Exhaust System

Silencer Grade : None Supplied  
Exhaust System Accessories : Bellows, System Fixing Kit

## Cooling System

Genset Mounted Radiator, 40C / 104F, Genset Mounted  
Engine Coolant Mixture : 50% Antifreeze, 50% Water

## Primary Electrical Isolation Device

None Supplied

## Entrance Box / Terminal Housing

Cable Entrance Box Required : Supplied  
Cable Entrance Box Location : Right  
Cable Entry Position : Set Mounted - Bottom Entry

## Control System Options

PowerCommand 3.3  
Control Panel Mounting (Viewed From Generator End) : End Facing  
Control Language : English  
Warning - Low Battery Voltage  
Shutdown - Low Coolant Level  
Meters - AC Output Analog  
Display - Control LCD  
Control Cabinet Heater : None Supplied

## Starting Batteries

Lead Acid Batteries - Dry Charged

## Battery Charger

Stand Alone / Wall Mountable, 5A, 240V

## Fuel Tank

None Supplied  
Fuel Tank Accessories  
Fuel Level Alarms : None Supplied

## Genset Testing

Genset Testing : Standard Factory Test  
Test Records : Certified Test

Warranty

Standby, 2 Years, 1000 Hours, Comprehensive Base Warranty

Literature Language

English

Packing

Cover - Shipping